$\epsilon$ 

Control Signal

MVA21 On-off 110...230 V~

(with cable)

MVA23 On-off 110...230V~

MVA actuators are used in V.ZB globe valve coupling for cool/warm

MVA actuators are electro-thermal type and are controlled by an on-off

Actuators are powered by control signal; this causes the thermostatic

element to heat up and a small piston to come out and, opposing to

MVA23-43 actuators are supplied with a microswitch mod. D41 with

contact closed by powered actuator; a particular application of fan control

terminal unit being: the fan, connected to microswitch contact on the actuator, operates by open valve and stops when valve is near to full

signal or, for MVA41/43 only, by pulse width modulation too.

water control in two- and four-pipe terminal units and zone systems.

MVA41 On-off PWM 24V~

(with cable)

MVA43 On-off PWM 24V~

APPLICATION AND USE

return spring, lower the valve stem.

**OPERATION** 



#### TECHNICAL CHARACTERISTICS

Power supply (control signal)

30 VA (fuse dimensioning)

Frequency 50/60 Hz

Cold start timing 2' (power-up to 1st stem movem.)

 Stroke time
 3' (opening)

 8' (closing)

 Max stroke
 3.5 mm

 min. force
 100 N

Temperature

 - working
 5T 50

 - storage
 -25T 65

 Protection class
 II (CEI 107-10)

Connection cable

(MVA21/41) 1.5 m (CEI 20-22/II)

Terminal board (MVA23/43) screw type for 1,5 to 2,5 mm<sup>2</sup>

conductors

Nr. 1 conduit opening

(MVA23/43) rubber, D=6 mm hole

Protection IP 31

For environments with normal pollution production after IEC 730-1 (93)/6.5.3

Weight 0.2 Kg

Product conforms to EMC 891336 directive with reference to the under

mentioned standards:

EN50081-1 for emission EN50082-1 for immunity

#### WORKING CHARACTERISTICS

close position. This in order to avoid cool air throw.

MVA actuators consist of a base and two thermoplastic (PA6 - 30% glass fiber) covers.

MVA21/41 models are fitted with supply cable.

APTC thermistor heats the thermal element inside actuators.

Actuators are equipped with a guillotine system allowing easy coupling to the valve by screw tightening.

### POSSIBLE COMBINATIONS AND CONNECTIONS

 $\ensuremath{\mathsf{MVA}}$  actuators are to be used with CONTROLLI V.ZB terminal and zone valves.

MVA21/23 actuators can be connected to any ON-OFF (110...230 V $\sim$ ) controller while MVA41/43 actuators can be connected both to any ON-OFF controller and to pulse width modulation controllers (24 V $\sim$ ); in particular with CONTROLLI RT700, DIGITROLL 7000, NR 7112/14 NR7312/14 controllers.

#### **ACCESSORIES**

D41 SPST 2(0,2) A - 250 V aux contact (only for MVA23/43) (contact closed when actuator is supplied)

Rev. f 07/00 1 DBL012E



Head-office: 16010 SANT'OLCESE Genova Italia Phone +39 01073061 Telefax +39 0107306870/871




#### **INSTALLATION AND ASSEMBLY**

For valve body coupling:

- remove plastic protection cover fitted on valve spring
- place actuator on valve body in the expected position (see ill. 1)
- tighten A screw
- connect the cable as per beside wiring diagram and instruction provided on the data sheets relavant to R.700 and DIGITROLL 7000 controllers.


# CAUTION: do not energize the actuator when it is not mounted on the valve body.

In order to ensure seal by valve closing, when coupling has been carried on, the actuator has to be powered for a few minutes so as to act a cycle.




CONNECTION CABLE (MVA21/41)

TERMINAL BOARD (MVA23/43)



#### N3049F1/F2

## ACTUATORS AND VALVE DIMENSIONS (mm)



N	4	0	2	6

Part Number	Ød	L	ØS	С	Н	h	Valve weight (kg)
VMZ09B/10B/11B/12B/13B/1B	G 1/2	66	42		169	112	0.45
VMZ2B	G 3/4	77	46		174	115	0.55
VSZ09B/10B/11B/12B/13B/1B	G ½	66	42		151	112	0.40
VSZ21B/2B	G 3/4	77	46		158	115	0.50
VSZ11BA/12BA/13BA/1BA	G 1/2	66	42		145	133	0.50
VSZ21BA/2BA	G 3/4	77	46		151	137	0.50
VTZ09B/10B/11B/12B/13B/1B	G 1/2	66	42	38	168	112	0.50
VTZ1BA	G 1/2	66	42	38	178	105	0.50
VTZ21B/2B	G 3/4	77	46	65	193	115	0.50

The performances stated on this sheet can be modified without any prior notice due to design improvement.

Rev.f 07/00 2 DBL012E

